



Battery Charging Station

The revolutionary RxChange™ Hot Swappable Battery Charging System is designed to provide true 24/7 mobility with Pioneer Mobile Touchscreen Computers (CT18M and CT22M). The Charging Station holds and charges up to 4 batteries at a time. We recommend having 2 batteries per touchscreen computer so one can charge while the other is in use. Keep the Battery Charging Station in a central location, ready to swap out batteries at a moments notice. Simply pull the handle up to release the battery, and drop the charged one in and you're ready to go. With a min. warranty of 1 year, the Battery Charging Station and Batteries are built and shipped from California, USA.

**Charging Station
for CT18M and CT22M**

Technical Specification

Charging Station

Charging Capacity:	4 Charging Bays Security Lock: Optional Mounting Options: Desktop
Dimensions:	5.79 x 5.71 x 8.98 in.
Operating Environment:	Temperature: 0C - 40C Humidity: 0% to 95%
Agencies:	CE, FCC
Weight:	GW: 3.74 lbs NW: 3.52lbs
Warranty:	One (1) year limited warranty

Batteries

Cell:	Lithium Ion
Capacity:	13400mAh
Dimensions:	5.55 x 2.91 x 1.54 in.
Operating Environment:	Temperature: 10C - 45C
Power Supply:	110V-240V, 2A
Input:	12.6V, 2.5A
Output:	10.8~11.1V, 5A
Warranty:	One (1) year limited warranty
Agencies:	CE, FCC, C-Tick
Weight:	1.44 lbs